

# Ersatzteilliste - Bill of Materials

<b>170151 P 1202 230V</b>	
Pos. Nr.	Best. Nr.
Ref. No.	Part No.
Bezeichnung	Description

Zubehör	Accessories & packaging material
---------	----------------------------------

359919	OWNER'S MANUAL P 1201/2	owner's manual
335589	FUSS-GUMMI SJ 5009 SW	rubber foot
300425	KABEL-NETZ 2.0 M 10A	power cable Europe
337053	SCHUTZHÜLLE 650X800X0,08	poly bag
306482	KRT. 2 HE 556X507X178	carton
357751	STYROPOR-EINLAGE X1201	filler, carton, foam
355742	STYROPOR-PL. 500X370X20	filler, carton, foam

Mechanische Teile	Cabinet material
-------------------	------------------

B0010	341343	BUCHSE-SPEAKON-VIERECK 4POL	speaker socket 4-pole
G0010	343270	GLRI GBPC 3504	rectifier GBPC-P 3504
S0010	346720	SCHALTER-NETZ ESB-99888V	power switch
	341382	KNOPF-TASTE 20X8 SW 3.3	push button black
	351214	GRIFF 109 MM GRAU 3HE	handle 109 mm
	348415	LÜFTER TYP FBA08A24H DC	fan dc 24V
	348387	KABEL-KONFEKT 10POL 0.300M	ribbon cable assy 10-way
	349610	KABEL-KONFEKT 10POL 0.520M	ribbon cable assy 10-way
	356956	KABEL-KONFEKT 12POL 0.320M	ribbon cable assy 12-way
	354999	KABEL-KONFEKT 12POL 0.350M	ribbon cable assy 12-way
	356957	KABEL-KONFEKT 4POL 0.420M	ribbon cable assy 4-way
	356663	KABEL-KONFEKT 14POL 0.250M	ribbon cable assy 14-way
	359960	FB.P 1202 BED	front panel P1202
	359961	RW.P 1202/230V BED	rear panel P1202
	351359	DEC.3HE-EV-LACK/P2-3000 LAC	top cover
	359917	BLEND.P1201/2 LEER LAC	blank panel
	359965	BLEND.O-1 BED	panel 0-1
	359966	BLEND.I-11 BED	panel I-11
	354550	NT-RG.Q66/S1200/CP2 230V	power transformer 230V
	348805	WI-SO PTC K155 100GRAD	safety component PTC
	348341	FEDERLEISTE 3POL CE100-	connector female 3-pole

<b>813448</b>	<b>PCBAR:X1201/X1202</b>	<b>N 5</b>	<b>input pcb assy</b>
---------------	--------------------------	------------	-----------------------

CN01Y	356660	STIFTLISTE 2X 7POL 1-	connector male 7x2 pins
C0003	340524	KO-EL 100.000MF 16V	cap electrolytic 100uF/16V
C0004	340524	KO-EL 100.000MF 16V	cap electrolytic 100uF/16V
C0005	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0006	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0501	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0502	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0503	301543	KO-KER 330.0PF 500V 10%	cap ceramic 330pF
C0504	301543	KO-KER 330.0PF 500V 10%	cap ceramic 330pF
C0505	301543	KO-KER 330.0PF 500V 10%	cap ceramic 330pF
C0506	301543	KO-KER 330.0PF 500V 10%	cap ceramic 330pF
C0507	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0508	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
C0509	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0510	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0511	346841	KO-EL 47.000MF 16V	cap electrolytic 47uF/16V
C0512	346841	KO-EL 47.000MF 16V	cap electrolytic 47uF/16V
C0513	340523	KO-EL 22.000MF 16V	cap electrolytic 22uF/16V
C0514	340523	KO-EL 22.000MF 16V	cap electrolytic 22uF/16V
C0515	340523	KO-EL 22.000MF 16V	cap electrolytic 22uF/16V
C0516	340523	KO-EL 22.000MF 16V	cap electrolytic 22uF/16V
C0517	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0518	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
D0501	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0502	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
H0001	343457	DICKS-NETZW. 8PIN 2%	res.network 8x10k Ohm
H0002	343457	DICKS-NETZW. 8PIN 2%	res.network 8x10k Ohm
I0501	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0502	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
JS501	351815	BUCHSE-FL. XLR 3POL PRINTB	xlr connector female 3-pole
JS502	351815	BUCHSE-FL. XLR 3POL PRINTB	xlr connector female 3-pole
JS503	351816	STECKER-FL. XLR 3POL PRINTB	xlr connector male 3-pin
JS504	351816	STECKER-FL. XLR 3POL PRINTB	xlr connector male 3-pin
R0515	329215	WI-SI 10.00 OHM 0.30W 5%	safety resistor 10.0 Ohm
R0516	329215	WI-SI 10.00 OHM 0.30W 5%	safety resistor 10.0 Ohm

<b>841938</b>	<b>PCBAR#X 1202</b>	<b>power amp pcb assy</b>
---------------	---------------------	---------------------------

CNAC1	343516	FL.STECKER 4.8/0.5	connector 4.8mm faston
CNAC2	343516	FL.STECKER 4.8/0.5	connector 4.8mm faston
CNA00	348802	MESSERLST. 12POL	connector male 12-pin
CNA01	348802	MESSERLST. 12POL	connector male 12-pin
CNB00	344975	MESSERLST. 10POL	connector male 10-pin
CNB01	344975	MESSERLST. 10POL	connector male 10-pin
CNGAC	343516	FL.STECKER 4.8/0.5	connector 4.8mm faston
CNGND	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CNL01	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CNL02	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CNN01	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CNN02	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CNRC1	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CNRC5	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CNSLA	352158	MESSERLST. 32POL	connector male 32-pin
CNSLB	352158	MESSERLST. 32POL	connector male 32-pin
CNS1X	354306	STIFTLEISTE 16POL	connector male 16-pin
CN001	348802	MESSERLST. 12POL	connector male 12-pin
CN002	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin
CN003	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin
CN004	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN005	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin
CN006	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN007	356660	STIFTLEISTE 2X 7POL 1-	connector male 7x2 pins
CN01X	348802	MESSERLST. 12POL	connector male 12-pin
CN012	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN014	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN015	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN018	341937	MESSERLST. 4POL	connector male 4-pin

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
CN019	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN020	344975	MESSERLST. 10POL	connector male 10-pin
CN18X	341937	MESSERLST. 4POL	connector male 4-pin
CN20X	344975	MESSERLST. 10POL	connector male 10-pin
C0001	342923	KO-FOL 0.220MF 63V 5%	cap mylar 220nF
C0002	307445	KO-EL 10.000MF 35V	cap electrolytic 10uF/35V
C0004	327366	KO-EL 4.700MF 50V BIP	cap bip electr. 4.7uF/50V
C0005	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0006	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0007	343530	KO-EL 47.000MF 50V	cap electrolytic 47uF/50V
C0008	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0011	354564	KO-EL 6800.000MF 100V	cap electr. 6800uF/100V
C0012	354564	KO-EL 6800.000MF 100V	cap electr. 6800uF/100V
C0013	354564	KO-EL 6800.000MF 100V	cap electr. 6800uF/100V
C0014	354564	KO-EL 6800.000MF 100V	cap electr. 6800uF/100V
C0015	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V
C0016	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0017	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0018	327366	KO-EL 4.700MF 50V BIP	cap bip electr. 4.7uF/50V
C0019	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0022	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0023	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0024	335935	KO-EL 2200.000MF 35V	cap electrolytic 2200uF/35V
C0025	335935	KO-EL 2200.000MF 35V	cap electrolytic 2200uF/35V
C0026	343530	KO-EL 47.000MF 50V	cap electrolytic 47uF/50V
C0027	343530	KO-EL 47.000MF 50V	cap electrolytic 47uF/50V
C0028	301524	KO-KER 47.0PF 500V 10%	cap ceramic 47pF
C0029	301524	KO-KER 47.0PF 500V 10%	cap ceramic 47pF
C0030	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0031	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0032	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V
C0036	346841	KO-EL 47.000MF 16V	cap electrolytic 47uF/16V
C0037	346841	KO-EL 47.000MF 16V	cap electrolytic 47uF/16V
C0038	346841	KO-EL 47.000MF 16V	cap electrolytic 47uF/16V
C0039	346841	KO-EL 47.000MF 16V	cap electrolytic 47uF/16V
C0040	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0041	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0042	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0043	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0044	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0045	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0046	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0047	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0048	346841	KO-EL 47.000MF 16V	cap electrolytic 47uF/16V
C0049	346841	KO-EL 47.000MF 16V	cap electrolytic 47uF/16V
C0050	346841	KO-EL 47.000MF 16V	cap electrolytic 47uF/16V
C0051	346841	KO-EL 47.000MF 16V	cap electrolytic 47uF/16V
C0052	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0100	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0101	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0102	301478	KO-EL 22.000MF 63V	cap electrolytic 22uF/63V
C0103	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0104	335787	KO-KER 15.0PF 100V 2%	cap ceramic 15pF
C0105	301458	KO-EL 2.200MF 63V	cap electrolytic 2.2uF/63V

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
C0106	327390	KO-FOL 470.000PF 100V 5%	cap mylar 470pF
C0107	340988	KO-FOL 0.470MF 63V 5%	cap mylar 470nF
C0108	301530	KO-KER 100.0PF 500V 10%	cap ceramic 100pF
C0109	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0110	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0111	342923	KO-FOL 0.220MF 63V 5%	cap mylar 220nF
C0112	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0113	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0114	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0115	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0116	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0117	351994	KO-KER 120.0PF 500V 2%	cap ceramic 120pF
C0118	351994	KO-KER 120.0PF 500V 2%	cap ceramic 120pF
C0119	301458	KO-EL 2.200MF 63V	cap electrolytic 2.2uF/63V
C0120	356605	KO-FOL 0.100MF 250V 5%	cap mylar 100nF
C0123	301519	KO-KER 10.0PF 500V 10%	cap ceramic 10pF
C0124	301519	KO-KER 10.0PF 500V 10%	cap ceramic 10pF
C0125	301474	KO-EL 22.000MF 16V BIP	cap bip electr. 22uF/16V
C0126	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0127	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0128	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0129	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0300	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0301	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0302	301478	KO-EL 22.000MF 63V	cap electrolytic 22uF/63V
C0303	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0304	335787	KO-KER 15.0PF 100V 2%	cap ceramic 15pF
C0305	301458	KO-EL 2.200MF 63V	cap electrolytic 2.2uF/63V
C0306	327390	KO-FOL 470.000PF 100V 5%	cap mylar 470pF
C0307	340988	KO-FOL 0.470MF 63V 5%	cap mylar 470nF
C0308	301530	KO-KER 100.0PF 500V 10%	cap ceramic 100pF
C0309	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0310	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0311	342923	KO-FOL 0.220MF 63V 5%	cap mylar 220nF
C0312	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0313	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0314	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0315	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0316	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0317	351994	KO-KER 120.0PF 500V 2%	cap ceramic 120pF
C0318	351994	KO-KER 120.0PF 500V 2%	cap ceramic 120pF
C0319	301458	KO-EL 2.200MF 63V	cap electrolytic 2.2uF/63V
C0320	356605	KO-FOL 0.100MF 250V 5%	cap mylar 100nF
C0323	301519	KO-KER 10.0PF 500V 10%	cap ceramic 10pF
C0324	301519	KO-KER 10.0PF 500V 10%	cap ceramic 10pF
C0325	301474	KO-EL 22.000MF 16V BIP	cap bip electr. 22uF/16V
C0326	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0327	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0328	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0329	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0519	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0520	340522	KO-EL 10.000MF 35V	cap electrolytic 10uF/35V
C0521	340522	KO-EL 10.000MF 35V	cap electrolytic 10uF/35V
D0002	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
D0003	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0004	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0005	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0006	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0007	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0008	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0009	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0010	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0011	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0014	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0015	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0016	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0017	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0018	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0019	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0020	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8
D0021	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8
D0022	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0023	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0100	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0101	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0102	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0104	329511	DIODZ BZX 55C 2V4 0.50W	diode zener 2V4
D0105	309450	DIODZ BZX 55C 15V 0.50W	diode zener 15V
D0106	309450	DIODZ BZX 55C 15V 0.50W	diode zener 15V
D0107	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0108	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0109	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0110	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0111	307916	DIODZ BZX 55C 7V5 0.50W	diode zener 7V5
D0112	307916	DIODZ BZX 55C 7V5 0.50W	diode zener 7V5
D0113	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0114	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0115	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0116	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0117	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0300	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0301	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0302	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0304	329511	DIODZ BZX 55C 2V4 0.50W	diode zener 2V4
D0305	309450	DIODZ BZX 55C 15V 0.50W	diode zener 15V
D0306	309450	DIODZ BZX 55C 15V 0.50W	diode zener 15V
D0307	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0308	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0309	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0310	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0311	307916	DIODZ BZX 55C 7V5 0.50W	diode zener 7V5
D0312	307916	DIODZ BZX 55C 7V5 0.50W	diode zener 7V5
D0313	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0314	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0315	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0316	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0317	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0503	354004	LED GN 3MM LOW CURRENT	led green

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
D0504	354003	LED RT 3MM LOW CURRENT	led red
D0505	354003	LED RT 3MM LOW CURRENT	led red
D0506	354005	LED GE 3MM LOW CURRENT	led yellow
D0508	354003	LED RT 3MM LOW CURRENT	led red
D0509	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0510	354004	LED GN 3MM LOW CURRENT	led green
D0511	354004	LED GN 3MM LOW CURRENT	led green
D0512	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
E0001	356594	RELAIS 793-P-1A-S-TV10	relay 24V / spst
E0100	354859	RELAIS	relay 24V
E0300	354859	RELAIS	relay 24V
F0001	302582	SICHER T 1.000 A/250V	fuse 1A slow blow
F0002	302582	SICHER T 1.000 A/250V	fuse 1A slow blow
F0003	302565	SICHER T 10.000 A/250V	fuse 10A slow blow
H0003	343456	DICKS-NETZW. 8PIN 2%	res.network 8x4k7 Ohm
H0004	343456	DICKS-NETZW. 8PIN 2%	res.network 8x4k7 Ohm
H0100	343456	DICKS-NETZW. 8PIN 2%	res.network 8x4k7 Ohm
H0101	343457	DICKS-NETZW. 8PIN 2%	res.network 8x10k Ohm
H0300	343456	DICKS-NETZW. 8PIN 2%	res.network 8x4k7 Ohm
H0301	343457	DICKS-NETZW. 8PIN 2%	res.network 8x10k Ohm
I0001	332985	IC TL 074 CN	IC TL 074 CN
I0003	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0004	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0005	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0100	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0101	307421	IC CA 3080 E OTA	IC CA 3080 E
I0102	332985	IC TL 074 CN	IC TL 074 CN
I0103	354919	IC OP 97 FP	IC OP 97
I0300	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0301	307421	IC CA 3080 E OTA	IC CA 3080 E
I0302	332985	IC TL 074 CN	IC TL 074 CN
I0303	354919	IC OP 97 FP	IC OP 97
JS001	338835	STECKER-KALTGERÄTE	connector male mains
L0100	348592	FILTERSP. 2.50UH/0.004OHM	coil 2.5uH
L0300	348592	FILTERSP. 2.50UH/0.004OHM	coil 2.5uH
Q0001	306928	TRANS BC 560 C	transistor BC 560 C
Q0002	306928	TRANS BC 560 C	transistor BC 560 C
Q0003	306928	TRANS BC 560 C	transistor BC 560 C
Q0004	306928	TRANS BC 560 C	transistor BC 560 C
Q0005	306928	TRANS BC 560 C	transistor BC 560 C
Q0008	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0009	301184	TRANS BC 550 C	transistor BC 550 B
Q0010	348591	TRANS BC 618 DARL. TO 92	transistor BC 618
Q0012	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0017	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0018	307430	TRANS BC 327-25 TO 92	transistor BC 327-25
Q0019	307430	TRANS BC 327-25 TO 92	transistor BC 327-25
Q0020	301235	TRANS BD 242 B	transistor BD 242 B
Q0021	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0022	301236	TRANS BD 241 B	transistor BD 241 B
Q0023	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0100	348421	TRANS 2N 3906	transistor 2N 3906
Q0101	335763	TRANS 2N 3904	transistor 2N 3904
Q0103	330264	TRANS J 111	transistor J 111 A

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
Q0104	335763	TRANS 2N 3904	transistor 2N 3904
Q0105	348421	TRANS 2N 3906	transistor 2N 3906
Q0106	348422	TRANS MPSA 42	transistor MPSA 42
Q0107	348423	TRANS MPSA 92	transistor MPSA 92
Q0108	335763	TRANS 2N 3904	transistor 2N 3904
Q0109	348421	TRANS 2N 3906	transistor 2N 3906
Q0110	348422	TRANS MPSA 42	transistor MPSA 42
Q0111	348423	TRANS MPSA 92	transistor MPSA 92
Q0112	335763	TRANS 2N 3904	transistor 2N 3904
Q0113	348421	TRANS 2N 3906	transistor 2N 3906
Q0114	335763	TRANS 2N 3904	transistor 2N 3904
Q0115	348421	TRANS 2N 3906	transistor 2N 3906
00010	338869	TRANS MJE 350	transistor MJE 350
00010	338868	TRANS MJE 340	transistor MJE 340
Q0118	348409	TRANS 2SC 4793	transistor 2SC 4793
Q0119	348421	TRANS 2N 3906	transistor 2N 3906
Q0120	335763	TRANS 2N 3904	transistor 2N 3904
Q0121	335763	TRANS 2N 3904	transistor 2N 3904
Q0122	348421	TRANS 2N 3906	transistor 2N 3906
Q0123	351981	TRANS MJL 3281 A	transistor MJL 3281 A
Q0124	351982	TRANS MJL 1302 A	transistor MJL 1302 A
Q0125	331657	TRANS MJ 15022	transistor MJ 15022
Q0126	331658	TRANS MJ 15023	transistor MJ 15023
Q0127	331657	TRANS MJ 15022	transistor MJ 15022
Q0128	331658	TRANS MJ 15023	transistor MJ 15023
Q0129	331657	TRANS MJ 15022	transistor MJ 15022
Q0130	331658	TRANS MJ 15023	transistor MJ 15023
Q0131	331657	TRANS MJ 15022	transistor MJ 15022
Q0132	331658	TRANS MJ 15023	transistor MJ 15023
Q0133	331657	TRANS MJ 15022	transistor MJ 15022
Q0134	331658	TRANS MJ 15023	transistor MJ 15023
Q0135	348422	TRANS MPSA 42	transistor MPSA 42
Q0136	348423	TRANS MPSA 92	transistor MPSA 92
Q0137	348423	TRANS MPSA 92	transistor MPSA 92
Q0138	348422	TRANS MPSA 42	transistor MPSA 42
Q0139	307911	TRANS BF 393	transistor BF 391
Q0140	307911	TRANS BF 393	transistor BF 391
Q0141	348423	TRANS MPSA 92	transistor MPSA 92
Q0142	348423	TRANS MPSA 92	transistor MPSA 92
Q0143	348421	TRANS 2N 3906	transistor 2N 3906
Q0144	348421	TRANS 2N 3906	transistor 2N 3906
Q0145	335763	TRANS 2N 3904	transistor 2N 3904
Q0146	306928	TRANS BC 560 C	transistor BC 560 C
Q0300	348421	TRANS 2N 3906	transistor 2N 3906
Q0301	335763	TRANS 2N 3904	transistor 2N 3904
Q0303	330264	TRANS J 111	transistor J 111 A
Q0304	335763	TRANS 2N 3904	transistor 2N 3904
Q0305	348421	TRANS 2N 3906	transistor 2N 3906
Q0306	348422	TRANS MPSA 42	transistor MPSA 42
Q0307	348423	TRANS MPSA 92	transistor MPSA 92
Q0308	335763	TRANS 2N 3904	transistor 2N 3904
Q0309	348421	TRANS 2N 3906	transistor 2N 3906
Q0310	348422	TRANS MPSA 42	transistor MPSA 42
Q0311	348423	TRANS MPSA 92	transistor MPSA 92

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
Q0312	335763	TRANS 2N 3904	transistor 2N 3904
Q0313	348421	TRANS 2N 3906	transistor 2N 3906
Q0314	335763	TRANS 2N 3904	transistor 2N 3904
Q0315	348421	TRANS 2N 3906	transistor 2N 3906
00010	338869	TRANS MJE 350	transistor MJE 350
00010	338868	TRANS MJE 340	transistor MJE 340
Q0318	348409	TRANS 2SC 4793	transistor 2SC 4793
Q0319	348421	TRANS 2N 3906	transistor 2N 3906
Q0320	335763	TRANS 2N 3904	transistor 2N 3904
Q0321	335763	TRANS 2N 3904	transistor 2N 3904
Q0322	348421	TRANS 2N 3906	transistor 2N 3906
Q0323	351981	TRANS MJL 3281 A	transistor MJL 3281 A
Q0324	351982	TRANS MJL 1302 A	transistor MJL 1302 A
Q0325	331657	TRANS MJ 15022	transistor MJ 15022
Q0326	331658	TRANS MJ 15023	transistor MJ 15023
Q0327	331657	TRANS MJ 15022	transistor MJ 15022
Q0328	331658	TRANS MJ 15023	transistor MJ 15023
Q0329	331657	TRANS MJ 15022	transistor MJ 15022
Q0330	331658	TRANS MJ 15023	transistor MJ 15023
Q0331	331657	TRANS MJ 15022	transistor MJ 15022
Q0332	331658	TRANS MJ 15023	transistor MJ 15023
Q0333	331657	TRANS MJ 15022	transistor MJ 15022
Q0334	331658	TRANS MJ 15023	transistor MJ 15023
Q0335	348422	TRANS MPSA 42	transistor MPSA 42
Q0336	348423	TRANS MPSA 92	transistor MPSA 92
Q0337	348423	TRANS MPSA 92	transistor MPSA 92
Q0338	348422	TRANS MPSA 42	transistor MPSA 42
Q0339	307911	TRANS BF 393	transistor BF 391
Q0340	307911	TRANS BF 393	transistor BF 391
Q0341	348423	TRANS MPSA 92	transistor MPSA 92
Q0342	348423	TRANS MPSA 92	transistor MPSA 92
Q0343	348421	TRANS 2N 3906	transistor 2N 3906
Q0344	348421	TRANS 2N 3906	transistor 2N 3906
Q0345	335763	TRANS 2N 3904	transistor 2N 3904
Q0346	306928	TRANS BC 560 C	transistor BC 560 C
Q0501	306928	TRANS BC 560 C	transistor BC 560 C
Q0502	348422	TRANS MPSA 42	transistor MPSA 42
Q0503	348422	TRANS MPSA 42	transistor MPSA 42
Q0504	301184	TRANS BC 550 C	transistor BC 550 B
Q0505	301184	TRANS BC 550 C	transistor BC 550 B
Q0506	306928	TRANS BC 560 C	transistor BC 560 C
Q0507	306928	TRANS BC 560 C	transistor BC 560 C
R0037	348490	WI-SO NTC K 164/100K/J	safety component NTC
R0065	348550	WI-SO NTC 10 OHM K	safety resistor 10 Ohm
R0185	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0188	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0191	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0194	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0197	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0208	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0209	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0223	341713	WI-DR 4.70 OHM 4.00W 5%	resistor 4.70 Ohm 4watt
R0225	341713	WI-DR 4.70 OHM 4.00W 5%	resistor 4.70 Ohm 4watt
R0227	341713	WI-DR 4.70 OHM 4.00W 5%	resistor 4.70 Ohm 4watt



Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
R0385	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0388	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0391	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0394	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0397	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0408	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0409	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0423	341713	WI-DR 4.70 OHM 4.00W 5%	resistor 4.70 Ohm 4watt
R0425	341713	WI-DR 4.70 OHM 4.00W 5%	resistor 4.70 Ohm 4watt
R0427	341713	WI-DR 4.70 OHM 4.00W 5%	resistor 4.70 Ohm 4watt
S0002	338886	SCHALTER-SCHIEBE L202-02-1-	switch slide
VR100	348486	WI-TRI 47.00 KOHM LIN	pot trim 47k Ohm lin
VR101	348674	WI-TRI 250.00 OHM LIN	pot trim 250 Ohm lin
VR300	348486	WI-TRI 47.00 KOHM LIN	pot trim 47k Ohm lin
VR301	348674	WI-TRI 250.00 OHM LIN	pot trim 250 Ohm lin
00030	303576	SICHER-HALTE-FEDER	fuse clip
00055	328390	SICHER-HALTER FAU	fuse holder
00065	328391	SICHER-HALTER-KAPPE FEK	fuse holder carrier